

Install


Activate

Talk

Install

- 1 Connect the enclosed Ethernet Cable from the BLUE Port on the DV Phone Adapter to your Xanadoo Wireless Modem.
- 2 Connect your current Ethernet Cable from your router or PC to the YELLOW Port on the DV Phone Adapter.
- 3 Using a phone cord, connect your phone and/or cordless base station to Phone 1 Port of the DV Phone Adapter.
IMPORTANT: Do not connect the phone cord from the DV Phone Adapter to a phone wall jack. The phone cord must be connected from your phone to one of the Phone Ports on the DV Phone Adapter.
- 4 Connect the enclosed Power Supply from the Power Port on the back panel of the DV Phone Adapter to a standard electrical outlet. The Phone 1 LED will be solidly lit when the DV Phone Adapter is properly installed.

Back of DV Phone Adapter



Activate

If you are a **NEW CUSTOMER** and purchased your DV Phone Adapter as part of a Xanadoo bundle, set up your Wireless Modem and DV Phone Adapter and launch your web browser. Follow the simple on-screen instructions to activate both your wireless high-speed internet and Digital Voice services.

If you are a **CURRENT CUSTOMER** and purchased your DV Phone Adapter separately, call Xanadoo Technical Support at 877.472.2911 to activate your Digital Voice service.

Talk

Your Xanadoo Digital Voice Unlimited is now connected. **Start talking and saving!**

Tech Support

Do you need help installing your DV Phone Adapter, have a question about activation or billing, call us toll free or visit us online at www.xanadoo.com

Technical Support

877.472.2911

Customer Support / Billing

866.733.9911

Login to **XANADOO.com** to

- Review features
- Check call history
- Review billing

Xanadoo
**Digital
Voice**

GET CONNECTED ON YOUR TERMS!

Digital Voice Service

Voicemail Instructions

Access Voicemail

1. Dial *36 from your phone
2. Enter your 4-digit PIN, followed by the # (pound) sign
3. To listen to messages - Press 1
 - Skip a message - Press 1
 - Save a message - Press 2
 - Erase a message - Press 3
 - Skip to start - Press 4
 - Pause/resume - Press 5
 - Skip to end - Press 6
 - Replay - Press 9
 - Exit menu - Press 0

Personalize Voicemail

1. Dial *36 from your phone
2. When prompted, enter your 4-digit PIN followed by the # (pound) sign
3. Press 8 for personal options, including the following:
 - Change your PIN - Press 1
 - Personalize your greeting - Press 2
 - Status check - Press 3
 - Call forwarding - Press 5
 - Record your personal name - Press 7
 - Repeat personal options - Press 9
 - Exit menu - Press 0

Remotely Access Voicemail

1. Dial your 10-digit phone number
2. When you hear your greeting, press the # (pound) sign
3. Enter your 4-digit PIN

Custom Quick Star Codes

Code	Description	Instructions
*30	Call Forwarding Enable/Disable	Forward to an extension in your account or a phone number
*31	Call Handling Status	Hear call forwarding status & other call handling features
*32	Voicemail Set-up	Set up or change voicemail pin & greeting (default pin: 1234)
*36	Voicemail	Access voicemail box & other features
*67	Block Caller ID	Blocks the caller ID for the call
*69	Call Return	Calls the last inbound caller
*70	Disable Call Waiting	Disable the call waiting on this call
Hook Flash	Call Waiting	Answers a second incoming call while placing the first call on hold
411	411 Service	Calls 411 information service
911	Emergency 911 Service	Calls emergency 911 service



GET CONNECTED ON YOUR TERMS!